

# **PM85** STAY ON TRACK WITH THE ALL-PURPOSE MOBILE COMPUTER

# Android zero-touch enrollment enabled by Google

Android zero-touch enrollment offers a seamless deployment method for corporate-owned Android devices making large scale roll-outs fast, easy and secure. Zero-touch makes it simple to configure devices online and have them shipped with enforced management so employees can open the box and get started. Enroll and deploy a wide variety of Android devices in bulk without any manual setup.

## **Ready for Any Rugged Task**

Qualcomm Snapdragon Octa-core processor runs at 1.8GHz for maximum computing. Memory options are available up to 4GB RAM and 64GB ROM, so there is plenty of space for programs, apps and personal data. It has an IP67 rating and is 1.8m drop proof to concrete (MIL-STD 810G), even the 5" IPS panel is equipped with shatter proof and scratch resistant capacitive Corning Gorilla glass.

### **Brand New Scanner Brings Enhanced Performance**

The new high-resolution scanner enhances reading performance, reading down to 3 mils resolution 1D barcodes with white LED illumination, which provides better readability of coloured barcodes and better imager capture results. It also supports OCR and EasyParse optional functions for driving licenses, boarding passes, and automotive part parsing for applications beyond barcodes.

# **Fully Equipped for Reliability**

Stay in touch with your workers with integrated LTE modem and Wifi support as well as dual speakers with 3W maximum output. PM85 supports band 28, the public protection and disaster recovery (PPDR) network frequency. The optional 4 Slot Battery Cradle provides ready-to-go devices across a variety of applications.

#### Industries

Retail Field Services Public Sector Transport & Logistics Hospitality

#### Accessories

Standard AC/DC Power Adaptor Country Plug USB Type-C Cable Standard Battery Handstrap LCD Protection Film

Extended Battery Single Slot Cradle (opt. Ethernet) Dual Slot Cradle \*Connect up to 3 Dual Slot Cradles to charge 6 devices at a time 4 Slot Battery Charger



-----

4 Slot Cradle (opt. Wall mount) Gun Handle (opt. UHF RFID) Stylus Pen

🕤 🎸



Optional

# **PM85**

| PERFORMA         |   |
|------------------|---|
| Main-Processor   |   |
|                  | agon @ 1.8GHz Octa-core                                     |
|                  |   |
| Operating System |   |
| Google Android   | Android 8.1 or 9.0  |
|                  | ) FOTA (Firmware Over The Air) update is                    |
|                  | available via MS Azure™ Cloud                               |
| Memory and Stora | ne  |
| RAM / ROM        | 3GB / 32GB or 4GB / 64GB (Optional)                         |
| Expansion Slot   | User accessible MicroSD up to 32GB SDHC                     |
|                  | and up to 256 GB SDXC                                       |
| SAM              | 2 Micro SAM slot  |
| SIM              | Dual-SIM card slot  |
| Sensor           | Gyroscope, Digital Compass,                                 |
|                  | Accelerometer, Light Ambient Sensor,                        |
|                  | Proximity Sensor  |
| PHYSICAL C       | HARACTERISTICS  |
| Dimensions (LxWx | D)  |
| STD batt.        | 157.6mm x 78mm x 18.86mm                                    |
|                  | 6.20in x 3.07in x 0.74in                                    |
| EXT batt.        | 157.6mm x 78mm x 23.26mm                                    |
|                  | 6.20in x 3.07in x 0.92in                                    |
| Weight           |   |
| STD batt.        | 256g / 9.03oz   |
| EXT batt.        | 315g / 11.11oz  |
| Display          | 5.0", IPS panel (1080 x 1920 pixel) FHD                     |
|                  | LED backlight   |
|                  | Daylight readable (500 nits typical)                        |
|                  | Wideviewing angle<br>Multi-touch capacitive                 |
|                  | Corning Gorilla glass                                       |
| Power            |   |
| STD              | 2,900mAh Li-ion rechargeable                                |
| EXT              | 5,800mAh Li-ion rechargeable                                |
| Back-up Battery  | 60mAh (10C) Li-ion rechargeable (Hot-Swap                   |
| 10 N             | 61 FM 2352 1355 1   |
| Keypad           | 9 physical keys<br>(All keys are programmable excluding the |
|                  | Power key)  |
| Voice and Audio  | Two built-in microphones (Noise-cancelling)                 |
| voice and Audio  | Dual speakers on front side (output max 3W)                 |
|                  | Receiver and headset jack (3.5mm)                           |
|                  | Bluetooth headset support                                   |
| Standard         | High speed USB 2.0  |
| Communications   | (supports battery charging PC, USB memory,                  |
|                  | digital headset)  |
| Notification     |   |
| LED              | Power (Charging, Battery Fault)                             |
|                  | Notification (Message, Scan)                                |
| Vibration        |   |
| Vibration        |   |

#### GPS

WiFi SKU : No GPS Phone SKU : Qualcomm GPS GNSS Receiver Support for A-GPS, GLONASS, Galileo, Beidou



| WIRELESS               |                                      |  |
|------------------------|--------------------------------------|--|
| Wireless WAN           |                                      |  |
| EDGE/GPRS/GSM<br>WCDMA | 900/1800/850/1900<br>B1/2/4/5/6/8/19 |  |

| EDEL/GPRS/GSM<br>WCDMA<br>LITE FDD<br>LITE TDD<br>2xCA support | 900/1800/850/1900<br>B1/2/3/4/5/7/8/19<br>B1/2/3/4/5/7/8/12/13/14/17/19/20/28<br>B38/B39/B40/41<br>B1+B5/B7/B8/B19<br>B3+B5//B8/B19<br>B2+B5/B17<br>B4+B7/17<br>B5+B7<br>Cat6, 300M DL/ 50M UL |
|--|--|
| Wireless LAN   |  |
| Radio  | IEEE 802.11a/b/g/n/ac/d/h/i/k/r/v,   |
| Data Rates   | IEEE 802.11a/n/ac: Up to 433 Mbps;<br>IEEE 802.11b/g/n: Up to 150 Mbps   |
| Operating  | 1 to 13 (2412~2472MHz),  |
| Channels   | 36 to 165 (5180~5825MHz)   |
| Channel<br>Bandwidth   | 20, 40, 80 MHz   |
| Security and<br>Encryption                                     | WEP(40 or 104bit)<br>WPA/WPA2 Personal(TKIP, AES);<br>WPA/WPA2 Enterprise(TKIP/AES) -<br>PEAP(MSCHAPv2, GTC),<br>TLS, TTLS(PAP, MSCHAP, MSCHAPv2, GTC)<br>PWD, SIM, AKA, AKA', LEAP            |
| Fast Roam  | CCKM, 802.11r  |
| Wireless PAN   |  |
| Bluetooth  | Integrated Bluetooth Class I, Ver. 5.0,<br>BLE support   |
| DATA CAPT  | JRE  |
| NFC (Near Field Co   | ommuncation)   |
| NFC-Forum  | Reader For NFC Forum (Tag Types 1 To 5),   |
| (NFC-IP MODES)   | P2P Active (106 To 424 kbps) Initiator and   |
|  | Target, P2P Passive(106 To 424 kbps)<br>Initiator and Target   |
|  |  |
| Reader   | ISO/IEC 14443 A, ISO/IEC 14443 B,  |
| (PCD - VCD)  | ISO/IEC 15693, Mifare Classic 1K/4K,<br>Mifare DESFire, Mifare UltraLight <sup>®</sup> , Sony FeliCa   |
| Camera   |  |
| Rear   | 13MP with LED flash  |
|  | 5MP  |

Honeywell N6603/3603 Slim Imager Engine (1D/2D barcode symbologies)

| USER ENVIRONMENT         |   |  |
|--------------------------|---|--|
| Operating<br>Temperature | -20°C to 60°C / -4°F to 140°F   |  |
| Storage<br>Temperature   | -25°C to 70°C / -13°F to 158°F  |  |
| Humidity                 | 95% Non-condensing  |  |
| Drop                     | 1.8m (6ft) multiple drops to concrete,<br>at room temp, based on MIL-STD 810G<br>1.5m (5ft) multiple drops to concrete,<br>across operating temperature range,<br>based on MIL-STD 810G |  |

Water / Dust Proof IP67 (Sealing)



| Tumble                     | 1,000 cycle (2,000hits) at 1m / 3.3ft  |
|----------------------------|--|
| Electrostatic<br>Discharge | ±15 kV air discharge<br>±8 kV contact discharge  |
| REGULATO                   | DRY APPROVALS<br>PLIANCE   |
| cUL, OTA, CTIA             | CU, FAC, "GCF, CEC, FCC, IC, PTCRB, KC, RCM,<br>RoHS III & WEEE compliant<br>Int   |
| ENTERPRI                   | SE SOLUTION  |
| SOTI, Airwatch, 7          | Feamviewer   |
| Scan2Stage                 | PC tool for provisioning Point Mobile<br>Android devices. With Scan2Stage, IT<br>administrator can prepare the settings of<br>the device and make QR code for<br>Scan2Set.   |
| EmKiosk                    | Kiosk application for Point Mobile<br>devices. IT administrator can restrict the<br>scope of the operator's system<br>execution via EmKiosk to increase<br>productivity and prevent distractions.                                      |
| Direct Clone               | Solution for restoring the devices to the<br>same settings with no internet<br>connection. With Direct Clone, a Master<br>PDA becomes a hotspot server and<br>sends its backup file to nearby client<br>devices to clone the settings. |

#### **PULS - ANDROID UPDATE & SECURITY**

PULS is Point Mobile's lifetime solution, which extends the life cycle of Android-based Point Mobile enterprise devices to up to seven years after a product launch.



Patches, Updates & Lifetime Support

Stay up-to-date with the latest updates for 7 years PULS comes free of charge for security patches & updates Get the latest Android version and its newest features Conveniently update your devices in the field by FOTA

For further information, please visit www.pointmobile.com or contact your regional sales representative.

#### WARRANTY

Subject to the Terms and Conditions, PM85 carries 1 (one) year-warranty period from the date of purchase against the defective materials and manufacturing defects.

For the further inquiry, please contact: service@pointmobile.com

# Nordelettronica S.R.L.

Via Cantù, 36 - 20092 - Cinisello Balsamo (MI) - Italia +39 02 6111961 - www.nordele.it - info@nordele.it

